

DigiTech RP500 Guitar Multi-FX Processor



Features

- 20-Second Looper-Full time, play, loop, change tones then overdub!
- Effect switching system offers control over internal stompboxes and effects
- Exclusive Pedalboard mode changes the RP500 into 5 individual stompboxes and effects
- Amp/Cabinet Bypass defeats internal amp and cabinet effects in all presets
- 40 Tone and 40 Effects Libraries
- 200 presets (100 factory, 100 user)
- Over 125 effects including stompboxes, choruses, delays, amps and cabinets
- Up to 5 seconds of delay time
- 24-bit 44.1kHz sample rate
- Heavy-duty metal switches for stompbox response
- Bright LEDs display program status and effect on / off
- Large 10 character LED display for preset name, bank name and tuner
- Built-in chromatic Tuner
- Independent XLR Left and Right Outputs with ground lift
- Independent 1/4" Left and Right Outputs
- Amp / Mixer switch to engage speaker cabinet
- Stereo 1/8" headphone output
- Stereo 1/8" CD/MP3 Input
- Built-in expression pedal controls the RP500's internal wahs, volume, Whammy™ and other parameters
- All metal construction
- Cubase LE4 Music Production Software included
- X-Edit Librarian Software included

- 2 x 2 USB audio streaming

Specifications

Chassis	Durable Cast Metal Construction
Display	Large 8 Character Alpha-numeric and 2 Character Numeric LED Display
A/D/A	24-bit high performance audio
Sampling Rate	44.1 kHz
DSP Section	AudioDNA2™ DSP Processor
Simultaneous Effects	10
Preset Memory	100 User Presets (1-00) / 100 Factory Presets (F1-F00)
Dimensions	19.5" Length x 8.625" Width x 2.75" Height
Unit Weight	6.6 lbs
USB Type	Type B, supports USB1.1 Full Speed (12 Mbps Bandwidth USB 2.0 compatible)
Power Supply	PS0913B

[DigiTech RP500 Guitar Multi-FX Processor Manual](#)