

Fender '65 Deluxe Reverb Combo Amp



ACCESSORIES

FOOTSWITCH: 2-Button Footswitch Included

ELECTRONICS

VOLTAGE: 120V

WATTAGE: 22 Watts

CONTROLS: Normal Channel: Volume, Treble, Bass. Vibrato Channel: Volume, Treble, Bass, Reverb. Vibrato: Speed, Intensity

CHANNELS: Two – (Normal and Vibrato)

INPUTS: Four – (1/4", Two Normal and Two Vibrato)

SPEAKER JACK: Two 1/4" Parallel (Internal and External)

HARDWARE

CABINET MATERIAL: 7-Ply 5/8" Birch Plywood

AMPLIFIER COVERING: Black Textured Vinyl

GRILLE CLOTH: Silver

AMPLIFIER JEWEL: Red Jewel

FRONT PANEL: Blackface™ Style

HANDLE: Molded Plastic Strap with Nickel-Plated Caps

SPEAKERS

SPEAKERS: One – 12" Jensen® C12K with Ceramic Magnet

TOTAL IMPEDENCE: 8 ohms

TUBES

PREAMP TUBES: 4 x 12AX7, 2 X 12AT7

POWER TUBES: 2 x 6V6

RECTIFIER: Tube (1 x 5AR4)

MEASUREMENTS

LENGTH (IN INCHES): 9.5

HEIGHT (IN INCHES): 17.5

WIDTH (IN INCHES): 24.5

WEIGHT (IN POUNDS): 42

UPC 717669051815