

Fender Super Champ X2 Combo Amp



Your rehearsal and recording sessions will really come alive with the unlimited tones that can be created with the Super Champ X2 combo, which takes one of Fender's most time-honored amps and ushers it into the present with updated style and modern modifications. Rocking 15 watts of dual-channel tube amp sound and a 10" speaker, the Super Champ X2 also delivers versatile amp voicing and a wide selection of digital effects. It's simple, toneful and flexible, with easy USB digital connectivity and Fender® FUSE™ software (available as a free download) for editing, preset storage, patch swapping and free artist content.

ACCESSORIES

FOOTSWITCH: Optional 2-Button Footswitch

ELECTRONICS

VOLTAGE: 120V

WATTAGE: 15 watts (Class AB)

CONTROLS: Volume 1, Channel Select, Gain, Volume 2, Voice, Treble, Bass, F/X
Adjust, F/X Select, Tap
CHANNELS: Two – Selectable
INPUTS: One – 1/4"
SPEAKER JACK: Two 1/4" Parallel (Internal and External)
LINE OUT: One – (1/4")

HARDWARE

AMPLIFIER COVERING: Black Textured Vinyl
GRILLE CLOTH: Silver
AMPLIFIER JEWEL: Red Jewel
HANDLE: Molded Plastic Strap with Nickel-Plated Caps

MISCELLANEOUS

LEGAL NOTICE: Product Prices, Features, Specifications and Availability Are
Subject To Change Without Notice

SPEAKERS

SPEAKERS: One – 10" Fender® Special Design
TOTAL IMPEDANCE: 8 ohms

TUBES

PREAMP TUBES: 1 x 12AX7
POWER TUBES: 2 x 6V6
RECTIFIER: Solid State

MEASUREMENTS

DEPTH (IN INCHES): 9.2
HEIGHT (IN INCHES): 15
WIDTH (IN INCHES): 17.5
WEIGHT (IN POUNDS): 24

PART NUMBER 2223000000

UPC 885978117536

[Fender Super Champ X2 Manual](#)